



CXone Mpower EXPERT

管理端口—e0M已关闭

https://kb-cn-stage.netapp.com/on-prem/ontap/OHW/OHW-KBs/Management_port_-_e0M_down

Updated: Wed, 22 Apr 2026 07:28:54 GMT

适用场景

- AFF 系统
- ASA 系统
- FAS 系统
- 服务处理器
 - [服务处理器 \(SP\)](#)
 - [基板管理控制器\(BMC\)](#)

问题描述

- 在ASUP的SYSCONFIG-A 中、SP以太网链路已关闭。

```
Service Processor      Status: Online
  Firmware Version:    5.1P4
  Mgmt MAC Address:    00:A0:98:BD:70:10
```

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

```
Ethernet Link:      down, 10Mb, half duplex
```

```
Using DHCP:        no
```

- ASUP的NETWORK-PORTS.XML 中的端口e0M也已关闭。
- 托管管理LIF的e0M端口 已关闭、事件日志中报告以下消息：

```
Wed Mar 24 08:40:25 IST [Node-name: mgmt_port_link_status_poll:  
netif.linkDown:info]: Ethernet e0M: Link down, check cable.
```

```
Wed Mar 24 08:40:35 IST [Node-name: vifmgr: vifmgr.port.monitor.failed:error]:  
The "link_flapping" health check for port e0M (node XXXX) has failed. The port  
is operating in a degraded state.
```

```
Wed Mar 24 08:41:05 IST [Node-name: vifmgr: vifmgr.portdown:notice]: A link  
down event was received on node Node-name, port e0M.
```

- 在与配对节点中的问题描述交换电缆后、此LUN仍会保留
- 将笔记本电脑直接连接到端口时、问题描述仍会保留
- 问题描述在关闭并重新打开服务处理器(SP)电源后仍然存在