



## E系列iSCSI连接频繁报告1815/1814/180d错误

[https://kb-cn-stage.netapp.com/on-prem/E-series/SANtricity-OS-Kbs/E-Series\\_iSCSI\\_connection\\_repor...](https://kb-cn-stage.netapp.com/on-prem/E-series/SANtricity-OS-Kbs/E-Series_iSCSI_connection_repor...)

Updated: Wed, 22 Apr 2026 08:48:42 GMT

### 适用场景

- NetApp E 系列
- iSCSI

### 问题描述

- 控制器报告以下错误：
  - Event type: 1815 iSCSI carrier has been lost
  - Event type: 1814 iSCSI carrier has been detected
  - Event type: 180D Session terminated unexpectedly
- `iscsi-statistics.csv` 在MAC **receive** statistics 中记录了大量CRC错误：

注：FCRCE = 帧CRC错误计数

- STATE-CAPTURE-DATA -> iscsiStateCapture -> showIscsiStats (ISCSI\_STATISTICS\_RAW) 下的错误计数器 指示所有错误均来自Rx (接收) :

```
=====  
ETHERNET PORT STATISTICS - PORT 0  
=====  
Port Rx Frame CRC Err Count 0xbdef6  
=====  
IP ENDPOINT STATISTICS - PORT 0  
=====  
IPV4 Received Pdus          0x0  
IPV4 Sent Pdus              0x0  
IPV4 Reassembly Required    0x0  
IPV4 Fragmentation          0x0  
IPV4 Fragmented Pdus Created 0x0  
IPV4 Tx Byte Count          0x0  
IPV4 Rx Byte Count          0x0  
IPV4 Rx Error Count         0x3eff
```

- 但目标端口(e0a)显示正常状态 :

```
Hostinterface:  iSCSI  
HostInterfaceCard(HIC):  Baseboard  
Channel:  1  
Port:  e0a  
Linkstatus:  Connected
```