



# CXone Mpower EXPERT

---

## Brocade FC交换机管理端口已关闭

[https://kb-cn-stage.netapp.com/on-prem/Switches/Brocade-KBs/Brocade\\_FC\\_Switch\\_Management\\_Po...](https://kb-cn-stage.netapp.com/on-prem/Switches/Brocade-KBs/Brocade_FC_Switch_Management_Po...)

Updated: Wed, 22 Apr 2026 11:39:20 GMT

### 适用场景

Brocade FC 交换机

### 问题描述

- Brocade管理端口不可访问、无发送或接收流量、错误转储中无错误表示硬件问题描述。
- 交换缆线和端口不会解决问题描述 问题
- 通过CLI检查Bro  
CADE交换机上的端口配置(串行连接):

```
switch:admin> ethif --show eth0
```

- \$ ethtool eth0  
Settings for eth0:  
Supported ports: [ TP MII ]  
Supported link modes: 10baseT/Half 10baseT/Full  
100baseT/Half 100baseT/Full

---

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

```
Supports auto-negotiation: Yes
Advertised link modes: 10baseT/Half 10baseT/Full
100baseT/Half 100baseT/Full
Advertised auto-negotiation: Yes
Speed: 100Mb/s
Duplex: Full
Port: MII
PHYAD: 1
Transceiver: external
Auto-negotiation: off
Link detected: no
```

- 如果端口设置为MII、请使用：

```
$ mii-tool -vvv:
[...]
eth0: 100 Mbit, full duplex, no link
[...]
basic mode: 100 Mbit, full duplex
basic status: no link
capabilities: 100baseTx-FD 100baseTx-HD 10baseT-FD 10baseT-HD
advertising: 100baseTx-FD 100baseTx-HD 10baseT-FD 10baseT-HD
```

- Cisco交换机上的已连接交换机端口：

```
#sh int status | in AB04
Gi1/0/15 AB04.AD.01 notconnect 666 full 1000 10/100/1000BaseTX
Gi1/0/16 AB04.AD.02 notconnect 666 full 1000 10/100/1000BaseTX
```