



CXone Mpower EXPERT

无法从磁盘所属节点中删除FlexArray磁盘所有权

https://kb-cn-stage.netapp.com/on-prem/ontap/OHW/OHW-KBs/Cannot_remove_Flexarray_disk_owne...

Updated: Wed, 22 Apr 2026 07:30:29 GMT

适用场景

- FAS8200
- E5600
- ONTAP 9.11.1P6
- FlexArray

问题描述

- 无法从拥有磁盘的节点中删除磁盘所有权
 - 运行 `removeowner` 命令时、会出现以下错误消息：

```
cluster::*> storage disk removeowner -disk NET-3.272
```

```
Error: command failed: Disk NET-3.272 is not connected to node05
```

- 无法取消分配磁盘、容器类型显示未知。

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

```
cluster::*> storage disk show -node node05
Usable Disk Container Container
Disk Size Shelf Bay Type Type Name Owner
-----
NET-3.272 - - - LUN unknown - node05
NET-3.130 - - - LUN unknown - node05
NET-3.131 - - - LUN unknown - node05
...
```

- 从nobeshell中、无法删除磁盘 所连接到的任一节点的磁盘所有权：

```
cluster:::> node run -node Node05
Node01> priv set diag
Node01*> disk remove_ownership <disk-path>
Node01*> disk show -n
Node01*> exit
```

- SYSCONFIG-A 输出表示FC主机适配器已建立链路、但驱动器未映射到 node05 拥有该磁盘的节点。

```
slot 2: FC Host Adapter 2a (Emulex XE201 rev. 48, N-port, <UP>) Board
name: 111-xxxxx Serial Number: FPxxxxxxxxx Firmware rev: 12.0.378.1 Host
Port Id: 0x3a0180 FC Node Name: 2:000:001xxx:xxxxxxx FC Port Name:
1:000:001xxx:xxxxxxx SFP Vendor: EMULEX SFP Part Number: AFBR-xxxxx-xxx SFP
Serial Number: AC1xxxxxx SFP Capabilities: 4, 8 or 16 Gbit Link Data Rate:
16 Gbit Switch Port: ?
```