



接管不可能：本地节点在 ONTAP 中缺少配对磁盘

https://kb-cn-stage.netapp.com/on-prem/ontap/OHW/OHW-KBs/Takeover_not_possible__local_node_...

Updated: Wed, 22 Apr 2026 10:27:42 GMT

适用于

- ONTAP 9
- AFF A800
- FAS9000

问题描述

- 更换磁盘后无法执行故障转移
- 节点报告无法执行故障转移。

```
Node: node01
Node Name as Returned by Storage Failover Component: node01
Partner Name: node02
Node NVRAM ID: XXXXXXXXXXXX
Partner NVRAM ID: XXXXXXXXXXXX
Takeover Enabled: true
```

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

```
HA Mode: ha
Takeover Possible: false
Reason Takeover not Possible: Local node missing partner disks
Reason Takeover not Possible (Enum value): disk_inventory_mismatch_local
Interconnect Up: true
Interconnect Links: RDMA Interconnect is up (Link up)
Interconnect Type: MVIA-RDMA
State Description: Connected to node02, Takeover is not possible: Local node
missing partner disks
Partner State: Up
```

- EMS 日志中的节点上存在与网络中断相对应的错误。

```
8/16/2023 20:37:50 node02 ERROR callhome.sfo.miscount: Call home for HA
GROUP ERROR: DISK/SHELF COUNT MISMATCH
8/16/2023 20:37:50 node02 ERROR cf.disk.inventory.mismatch: Status of the
disk 0f.21
(32343637:65386464:00000000:00000000:00000000:00000000:00000000:00000000:00000000)
has recently changed or the node (node02) is missing the disk.
8/16/2023 20:37:50 node02 ERROR cf.disk.inventory.mismatch: Status of the
disk 0f.22
(33376335:37306161:00000000:00000000:00000000:00000000:00000000:00000000:00000000)
has recently changed or the node (node02) is missing the disk.
```

- 拥有磁盘的合作伙伴节点报告它们运行状况良好。
- 更换磁盘未解决问题。