



CXone Mpower EXPERT

由于交换机上的分区配置不当、VM出现停机

https://kb-cn-stage.netapp.com/on-prem/Switches/Broadcom-KBs/VM_experienced_downtime_due_to...

Updated: Wed, 22 Apr 2026 10:27:40 GMT

适用场景

- Brocade光纤交换机
- VMware主机

问题描述

- 在网络结构中重新启动交换机后、VM关闭、导致存储无法访问。
- 与受影响VMware主机关联的所有交换机端口均处于联机状态，交换机端口的RX、TX值处于最佳范围。

| Index | Port | Address | Media | Speed | State | Proto | | |
|-------|------|---------|-------|-------|--------|-------|--------|-------------------------|
| 0 | 0 | 010000 | id | N16 | Online | FC | F-Port | 50:06:01:6d:xx:xx:xx:xx |
| 1 | 1 | 010100 | id | N16 | Online | FC | F-Port | 50:06:01:69:xx:xx:xx:xx |

- 在网络结构中的两个交换机上验证分区。

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

- 以下示例显示了与指定分区名称匹配或部分匹配的已验证分区成员：

```
switch:admin> zoneshow --validate zone1
Defined configuration:
  zone:   zone1   20:1c:00:05:xx:xx:xx:xx*; 20:1d:00:05:xx:xx:xx:xx

Effective configuration:
  zone:   zone1   20:1c:00:05:xx:xx:xx:xx*
           20:1d:00:05:xx:xx:xx:xx
-----
~ - Invalid configuration
* - Member does not exist
```