



CXone Mpower EXPERT

Brocade 交换机上记录了 "IT_FLOW" 事件

https://kb-cn-stage.netapp.com/on-prem/Switches/Brocade-KBs/IT_FLOW_events_logged_on_Brocad...

Updated: Wed, 22 Apr 2026 09:00:27 GMT

适用场景

Brocade 交换机上的端口

问题描述

- “IT-FLOW”事件记录在 Brocade 交换机上的 errdump 下：

```
2023/06/18-00:00:16:536399 (IST), [MAPS-2938], 862272/753764, SLOT 2 | FID 128,
WARNING, BROCADESW, Pid 0x6fc5xx, Condition=ALL_LOCAL_PIDS(IT_FLOW/NONE>16), Current
Value:[IT_FLOW, 37 IT-Flow(s)], RuleName=defALL_LOCAL_PIDSIT_FLOW_16, Dashboard
Category=Fabric Performance Impact, Quiet Time=None., raslogAction.c, line: 218,
comp:md, ltime:2023/06/18-00:00:16:536221
2023/06/18-00:00:16:537623 (IST), [MAPS-2938], 862273/753765, SLOT 2 | FID 128,
WARNING, BROCADESW, Pid 0x6f7dxx, Condition=ALL_LOCAL_PIDS(IT_FLOW/NONE>16), Current
Value:[IT_FLOW, 47 IT-Flow(s)], RuleName=defALL_LOCAL_PIDSIT_FLOW_16, Dashboard
Category=Fabric Performance Impact, Quiet Time=None., raslogAction.c, line: 218,
```

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

comp:md, ltime:2023/06/18-00:00:16:537440

- defIT_RES_USAGE_P_75 映射警报已触发：
- 从mapsdb --show 输出中，我们可以看到dflt_moderate_policy 是**Active**策略。

1 Dashboard Information:

=====

DB start time: Mon May 15 22:10:32 2023

Active policy: dflt_moderate_policy

Configured Notifications:

RASLOG, SNMP, SW_CRITICAL, SW_MARGINAL, SFP_MARGINAL, SDDQ, UNQUAR, RE_BALANCE

Fenced Ports : None

Decommissioned Ports : None

Fenced circuits : None

Quarantined Ports : None

**Top Zoned PIDs <pid(it-flows)>: 0x6f6dxx(60) 0x6f6cxx(60) 0x6fcbyx(60) 0x6f2dxy(60)
0x6fcbyy(60)**

- 在上述mapsdb --show 输出中、它还会显示具有最高IT_flow比率的PID/终端设备。 这些信息也会显示在errdump 下的错误日志中。

2023/06/18-00:00:16:537623 (IST), [MAPS-2938], 862273/753765, SLOT 2 | FID 128, WARNING, BROCADESW, **Pid 0x6fcbyy**, Condition=ALL_LOCAL_PIDS(IT_FLOW/NONE>16), Current Value:[IT_FLOW, 47 IT-Flow(s)], RuleName=defALL_LOCAL_PIDSIT_FLOW_16, Dashboard Category=Fabric Performance Impact, Quiet Time=None., raslogAction.c, line: 218, comp:md, ltime:2023/06/18-00:00:16:537440