



## 具有 ChangeNotify 的 CIFS FlexGroup 无响应

[https://kb-cn-stage.netapp.com/on-prem/ontap/Perf/Perf-KBs/CIFS\\_FlexGroups\\_with\\_ChangeNotify\\_b...](https://kb-cn-stage.netapp.com/on-prem/ontap/Perf/Perf-KBs/CIFS_FlexGroups_with_ChangeNotify_b...)

Updated: Wed, 22 Apr 2026 10:26:09 GMT

### 适用场景

ONTAP 9.2 或更高版本

### 问题描述

- FlexGroup 或 LUN 上会出现多秒的延迟
- 由于 LUN 无法读取或写入，SAN 通信变得无响应
  - 高延迟与 `qos statistics` 类似：

```
Cluster::> qos statistics latency show -node node1 Policy Group Latency Network Cluster Data Disk
QoS Max QoS Min NVRAM Cloud FlexCache SM Sync VA -----
----- -total- 10.44s 10.44s 38.00us
0ms 0ms 0ms 0ms 0ms 0ms 0ms 0ms 0ms 0ms policy_group_1 18.03s 18.03s 72.00us 0ms 0ms 0ms 0ms
0ms 0ms 0ms 0ms 0ms
```

- 事件日志消息可能如下所示：

'NetApp provides no representations or warranties regarding the accuracy or reliability or serviceability of any information or recommendations provided in this publication or with respect to any results that may be obtained by the use of the information or observance of any recommendations provided herein. The information in this document is distributed AS IS and the use of this information or the implementation of any recommendations or techniques herein is a customers responsibility and depends on the customers ability to evaluate and integrate them into the customers operational environment. This document and the information

```
Mon Aug 09 21:18:15 +0800 [node1: kernel: Nblade.cifsLockStateMismatch:debug]: params: {'pMessage':  
'Leaked share lock?'} Mon Aug 09 21:19:38 +0800 [node1: kernel: Nblade_CifsOperationTimedOut_  
1:error]: params: {'remoteBladeID': '12345678-9012-3456-7890-123456789012 (node1)', 'cmdRestartCnt':  
'0', 'vserverId': '4', 'commandName': 'SMB2_COM_CREATE', 'isQosEnabled': 'QoS_disabled',  
'lastSpinNpError': 'SPINNP_NO_FO_ERROR', 'localIpAddress': '10.1.2.3', 'lastCsmError': 'CSM_TIMEOUT',  
'clientIpAddress': '10.2.3.4', 'suspensionCnt': '7', 'dsId': '0'}
```